

Q usl-

- Cloud Gateways
- Switching
- WiFi
- Camera Security
- Door Access
- Integrations
- Advanced Hosting
- Accessories

Special Devices > [Entry Sensor](#)

Datasheet

In The Box

Marketing Images

Installation Guide



^ Overview

Dimensions Device: 75.5 x 23.5x 22.5 mm (3 x 0.93 x 0.89") Magnet: 39 x 15.1 x 12.9 mm (1.5 x 0.6 x 0.5")

Mounting Adhesive and screw mount

UniFi Application Suite

Protect ✓

^ Performance

Connectivity SuperLink (Proprietary)

Operating Frequency

US 915.6-927.6 MHz

EU 865.1-869.5 MHz

Antenna Gain

SuperLink 0 dBi

Max. TX Power

SuperLink 14 dBm

Max. Range

SuperLink 2 km (1.2 mi)

Sensor Features

Reed Switch ✓

^ Hardware

Max. Power Consumption 27.7mW

Supported Voltage Range 3V

Power Method Lithium battery CR123A

Battery Life Up to 6 years

Weight Device: 41 g (1.4 oz) Magnet: 22 g (0.8 oz)

Enclosure Material Polycarbonate

Mount Material	Polycarbonate
Buttons	(1) Factory-reset (1) Function button (1) Tamper switch
LEDs	(1) Status: R/B/W (1) Signal: B/R
Ambient Operating Temperature	0 to 40° C (32 to 104° F)
Ambient Operating Humidity	10 to 90% noncondensing
Certifications	FCC, IC, CE
NDA Compliant	✓
^ Software	
Application Requirements	
Web Application	UniFi Protect
Mobile App	UniFi Protect iOS™ and Android™

Stay in Touch

 

[Terms of Service](#) | [Privacy Policy](#) | [Legal](#) | [Cookies Settings](#)

© 2025 Ubiquiti, Inc. All rights reserved.